

# Video Converter

## SDI/HDMI Bidirectional

### TXVV-SDIXHDMI

Professional equipment in mission-critical applications is all about reliability and confidence. So we started with a clean sheet, and built what might soon become your most trustworthy piece of equipment.

Introducing the world's first video converters *truly* designed for the road. Video converters nowadays are used everywhere on professional A/V events, presentations, live shows and tours and often have a critical role. Yet, they are often the weakest link in the signal chain. Low quality connectors, weak enclosure, external consumer-grade power supply, and overall barebones design that all contribute to a generally unreliable piece of equipment. We wanted to change that, so we designed the xVision Video Converters.





DESIGNED & MANUFACTURED  
IN CANADA




## Features

- ✓ **Integrated power supply** with locking PowerCON connector. Never rely on a cluster of wall-warts again.
- ✓ **Built-in convenience 120V** outlet to power nearby projector, TV, laptop, small video projector... Power bar to power both the converter and device not required anymore.
- ✓ **Magnetic stacking system** and non-skid rubber pad. Saves at least 10 gaffer tape rolls a year.
- ✓ **Multiple mounting options:** C-Clamp, wall-mount adapter, LCD mount adapter and belt adaptor.
- ✓ **Rugged, Tour-ready and aesthetic enclosure:** The sexiest widget in your tool box, that will keep looking good for years to come.
- ✓ **Plug-n-play operation**; No dipswitches, buttons or menus to fumble with: It just works.
- ✓ Clear and ample status **LED indicators** for quick troubleshooting.
- ✓ **Easy on-the-field identification** with unique color and alphabetic coding system.
- ✓ **Locking HDMI ports** prevent accidental disconnection.
- ✓ **Reclocked and amplified SDI** outputs.
- ✓ Proudly designed and assembled **in Canada**.
- ✓ The only converter you'll need: **SDI to HDMI or HDMI to SDI** with **automatic** incoming signal type detection.



Connections

- Video Input** Auto switching between: 3G/HD/SD SDI  
BNC & HDMI 1.2 type A with lock system
- Video Output**
- HDMI 1.2 type A with lock system
  - 2 x 3G/HD/SD SDI BNC
- Input Priority** SDI input



Supported Signals

- 3G Format Support** 1080p50, 1080p59.94, 1080p60.
- HD Format Support** 720p50, 720p59.94, 720p60, 1080i50, 1080i59.94, 1080i60, 1080p23.98, 1080PsF23.98, 1080p24, 1080PsF24, 1080p25, 1080PsF25, 1080p29.97, 1080PsF29.97, 1080p30, 1080PsF30
- SD Format Support** 525/23.98 NTSC, 525/29.97 NTSC.625/25 PAL
- SDI Video Sampling** 4:2:2 and 4:4:4
- SDI Audio Sampling** Sample rate of 48 kHz and 24 bit
- SDI Color Space** YUV and RGB
- SDI Auto Switching** Automatically detects incoming signal format

Physical Specifications

- Height** 50 mm (1.97 in)
- Depth** 180 mm (7.08 in)
- Width** 107 mm (4.21 in)
- Weight** 1 kg (2.2 lbs)

Environnemental Specifications

- Relative Humidity** 0% to 90 % non-condensing

Power Requirements

- Power Supply** Built-in power supply  
PowerCON input  
Edison Nema 5-15 output
- Power Consumption** 25W
- Operational Voltage Range** 90-125V  
90-250V also available (with PowerCON True1)
- Courtesy Outlet** Max 10A, same voltage as input

- In the box**
- xVision converter SDI to HDMI
  - HDMI male with locking system to DVI male (1m)
  - Edison to PowerCON (1m)

- Certification** CAN/CSA-C22.2 NO. 60950-1-07  
UL 60950-1  
FCC Part 15 Class A

Ordering information

- TXVV-HDMI2SDI** .....xVision HDMI to SDI converter
- TXVV-SDI2HDMI** .....xVision SDI to HDMI converter
- TXVV-SDIDA** .....xVision SDI Distribution Amplifier (4 outputs)
- TXVV-SDI2AUDIO** .....xVision SDI Audio DeEmbedder
- TXVV-AUDIO2SDI** .....xVision Video Converter SDI Audio Embedder

- TXVV-SDIXHDMI** .....xVision Video Converter SDI/HDMI to HDMI+SDI
- XVV-CC1** .....xVision Video Converter Carrying Case for 1 unit
- XVV-CC2** .....xVision Video Converter Carrying Case for 2 units
- XVV-CC3** .....xVision Video Converter Carrying Case for 3 units