

Shot Box² - Ref. SB80-2

Cost effective solution to easily control the Presets on **LiveCore™** and **Midra™** series



Shot Box² at a glance

- ▶ 76 function-labeled keys
- ▶ Customizable blue and red backlighting
- ▶ Readily operational on all **LiveCore™** series and **Midra™** series via the **RCS²** software
- ▶ USB connection to PC or Mac

Key features

- ▶ **User Controls**
 - 70 keys to load instantly Master presets, Screen presets or Confidence Screen presets (up to 140 presets available for **LiveCore™** series and up to 64 presets available for **Midra™** series)
 - 4 keys for the Customizable Monitoring/Preview (8 presets available: **LiveCore™** series only)
 - 1 large key for the Page selection (**LiveCore™** series only)
 - 1 large key for the Take button
- ▶ **Connectors**
 - 1 USB connector

To Control the following Switchers

LiveCore™ series

- ▶ ASC4806-4K-PL: Ascender 48 - 4K - PL*
 - ▶ ASC3204-4K-PL: Ascender 32 - 4K - PL*
 - ▶ ASC1602-4K: Ascender 16 - 4K*
 - ▶ SMX12x4: SmartMatrix Ultra
 - ▶ NXT1604-4K: NeXtage 16 - 4K*
 - ▶ NXT0802-4K: NeXtage 08 - 4K*
- *Non-4K units are supported

Midra™ series


- ▶ EKS550: Eikos²
- ▶ SPX450: Saphyr
- ▶ SMX250: SmartMatrix²
- ▶ PLS350: Pulse²
- ▶ PLS350-3G: Pulse²
- ▶ QMX150: QuickMatrix
- ▶ QVU150: QuickVu
- ▶ QVU150-3G: QuickVu

LiveCore™ series

- | | |
|------------------------------------|---|
| NeXtage 08 - 4K
Ref. NXT0802-4K | Ascender 16 - 4K
Ref. ASC1602-4K |
| NeXtage 16 - 4K
Ref. NXT1604-4K | Ascender 32 - 4K - PL
Ref. ASC3204-4K-PL |
| SmartMatrix Ultra
Ref. SMX12x4 | Ascender 48 - 4K - PL
Ref. ASC4806-4K-PL |

Midra™ Series

- | | | |
|-----------------------------------|---|---|
| Eikos ²
Ref. EKS550 | Saphyr
Ref. SPX450 | SmartMatrix ²
Ref. SMX250 |
| Pulse ²
Ref. PLS350 | QuickMatrix ²
Ref. QMX250 | QuickVu
Ref. QVU150 |



NOTE

Connect the Shot Box² USB cable directly to your computer - Do not connect the Shot Box² USB cable to the USB port of your **LiveCore™/Midra™** series.

Dimensions:

- ▶ D 7.25" x W 8.25" x H 0.94"
- ▶ D 184 mm x W 210 mm x H 240 mm

Weight:

- ▶ 0,726 kg
- ▶ 1.6 lbs

Supplied with:

- ▶ 1 x Carrying case
- ▶ 1 x USB stick containing both the Windows and MAC OS setup applications*
- ▶ 1 x Quick Start Guide*

Warranty:

1-year warranty on parts and labor back to factory.



* The Quick Start Guide and the External Software are also available on www.analogway.com

① Specifications subject to change without prior notice

All technical specifications are available on our website

Follow us    

Europe, Middle East and Africa - ANALOG WAY SAS - Tel: +33 (0)1 81 89 08 60 / Fax: +33 (0)1 57 19 04 54 / Email: saleseuro@analogway.com
 The Americas - ANALOG WAY Inc. - Tel: +1 (678) 487 6644 / Fax: +1 212 269 1943 / Email: salesusa@analogway.com
 Asia Pacific - ANALOG WAY Pte Ltd - Tel: +65 62 92 58 00 / Fax: +65 62 92 52 05 / Email: sales@analogwayasia.com

SB80-2-uk-12/27/2016



ANALOG WAY®
Pioneer in Analog. Leader in Digital